## NG4-VCMR2D470D00



NG4access® Module VAM, CWDM, 8 channels, upgrade port, 1310 nm port, 2 circuits, LC/APC, right, 1471 nm starting channel, no test ports

- VAMs help enhance optical transport systems by providing flexible, easy to incorporate optical components into the network
- VAMs increase fiber capacity and help troubleshooting or distributing signals to multiple subscribers
- \*Product complies with the Build America, Buy America Act (BABAA) requirements of the Infrastructure Investment and Jobs Act of 2021 (Pub. L. 117- 58, §§ 70901-70953), or is the subject of a waiver approved by the Secretary of Commerce or designee. Compliance requirements and waiver applicability vary based on government funding program. Check the laws and regulations for your specific program.

#### Product Classification

Regional Availability Latin America | North America

PortfolioCommScope®Product TypeCWDM moduleProduct BrandNG4access®Product SeriesFACT | NG4

**Government Funding**Build America Buy America (BABA) compliant\*

### General Specifications

**Device Type** Plug-and-play module

**Functionality** Multiplexing

**Application** For use with NG4 access frames

Circuits, quantity 2

**Distribution Type** 8-channel CWDM

Interface, frontLC/APCInterface, InputLC/APCInterface, OutputLC/APC

Multiplexers, quantity 2

Port Type, optional 1310 nm port | Upgrade port

**Tray Orientation** Right orientation

Dimensions

COMMSCOPE®

# NG4-VCMR2D470D00

Height 13.21 mm | 0.52 in Width 159.77 mm | 6.29 in **Depth** 130.3 mm | 5.13 in

### **Optical Specifications**

**Starting Channel Number** 47

**Starting Wavelength** 1471 nm

### Packaging and Weights

**Packaging quantity** 

