

3.0m | 10ft Sentinel® Ultra High Performance, Super High XPD Antenna, dual-polarized, 12.200 – 13.250 GHz

#### **Product Classification**

Product Type Microwave antenna

General Specifications

Antenna Type USX - Sentinel® Ultra High Performance, Super

High XPD Antenna, dual-polarized

**Polarization** Dual

Side Struts, Included 2

Side Struts, Optional 3

**Dimensions** 

**Diameter, nominal** 3.0 m | 10 ft

**Electrical Specifications** 

Operating Frequency Band 12.200 – 13.250 GHz

Gain, Low Band48.5 dBiGain, Mid Band48.8 dBi

**Gain, Top Band** 49.2 dBi

Boresite Cross Polarization Discrimination (XPD) 40 dB
Front-to-Back Ratio 82 dB

Beamwidth, Horizontal 0.6 °

Beamwidth, Vertical 0.6 °

Return Loss 26 dB

**VSWR** 1.1

Radiation Pattern Envelope Reference (RPE) 7427

Electrical Compliance ACMA FX03\_13a | ETSI 302 217 Class 3 | US

FCC Part 101A

Cross Polarization Discrimination (XPD) Electrical Compliance ETSI EN 302217 XPD Category 3

Mechanical Specifications


**COMMSCOPE®** 

Compatible Mounting Pipe Diameter115 mm | 4.5 inFine Azimuth Adjustment Range±5°Fine Elevation Adjustment Range±5°Wind Speed, operational180 km/h | 111.847 mphWind Speed, survival200 km/h | 124.274 mph



## Antenna Dimensions and Mounting Information

#### USX10



Dimensions in inches (mm)						
Antenna Size, ft (m)	А	В	С	D	E	F
10 (3)	8.0 (203)	22.5 (572)	125.0 (3174)	38.6 (980)	71.1 (1807)	10.3 (262)

## Wind Forces at Wind Velocity Survival Rating

Axial Force (FA)

Angle  $\alpha$  for MT Max

Side Force (FS)

Twisting Moment (MT)

Force on Inboard Strut Side

**Force on Outboard Strut Side** 

Zcg without Ice

Zcg with 1/2 in (12 mm) Radial Ice

18800 N | 4,226.409 lbf

-130°

-6560 N | -1,474.747 lbf

-10725 N-m | -94,924.25 in lb

9500 N | 2,135.686 lbf

3350 N | 753.11 lbf

618 mm | 24.331 in

744 mm | 29.291 in


COMMSC PE°

Weight with 1/2 in (12 mm) Radial Ice

466 kg | 1,027.353 lb



## Wind Forces at Wind Velocity Survival Rating Image



#### Packaging and Weights

**Weight, net** 263 kg | 579.815 lb

\* Footnotes

**Operating Frequency Band** 

Gain, Mid Band

**Boresite Cross Polarization Discrimination (XPD)** 

Bands correspond with CCIR recommendations or common allocations used throughout the world. Other ranges can be accommodated on special order.

For a given frequency band, gain is primarily a function of antenna size. The gain of Andrew antennas is determined by either gain by comparison or by computer integration of the measured antenna patterns.

The difference between the peak of the co-polarized main

Page 5 of 7



Front-to-Back Ratio

**Return Loss** 

**VSWR** 

beam and the maximum cross-polarized signal over an angle twice the 3 dB beamwidth of the co-polarized main beam.

Denotes highest radiation relative to the main beam, at 180° ±40°, across the band. Production antennas do not exceed

rated values by more than 2 dB unless stated otherwise.

The figure that indicates the proportion of radio waves incident upon the antenna that are rejected as a ratio of

those that are accepted.

Maximum; is the guaranteed Peak Voltage-Standing-Wave-

Ratio within the operating band.

Radiation Pattern Envelope Reference (RPE)

Radiation patterns define an antenna's ability to discriminate

against unwanted signals. Under still dry conditions, production antennas will not have any peak exceeding the current RPE by more than 3dB, maintaining an angular

accuracy of +/-1° throughout

Cross Polarization Discrimination (XPD) Electrical Compliance The difference between the peak of the co-polarized main

beam and the maximum cross-polarized signal over an angle twice the 3 dB beamwidth of the co-polarized main beam.

Wind Speed, operational For VHLP(X), SHP(X), HX and USX antennas, the wind speed

where the maximum antenna deflection is 0.3 x the 3 dB beam width of the antenna. For other antennas, it is defined

as a deflection is equal to or less than 0.1 degrees.

Wind Speed, survival

The maximum wind speed the antenna, including mounts

and radomes, where applicable, will withstand without permanent deformation. Realignment may be required. This wind speed is applicable to antenna with the specified

amount of radial ice.

**Axial Force (FA)**Maximum forces exerted on a supporting structure as a

result of wind from the most critical direction for this parameter. The individual maximums specified may not occur simultaneously. All forces are referenced to the

mounting pipe.

**Side Force (FS)**Maximum side force exerted on the mounting pipe as a

result of wind from the most critical direction for this parameter. The individual maximums specified may not occur simultaneously. All forces are referenced to the

mounting pipe.

**Twisting Moment (MT)**Maximum forces exerted on a supporting structure as a

result of wind from the most critical direction for this

Page 6 of 7

parameter. The individual maximums specified may not occur simultaneously. All forces are referenced to the mounting pipe.