2P-2L-C1



2-port sector antenna, 2x 694–960 MHz, 65° HPBW, 1x RET

• Utilizes RET-PMOD-A20-1A01

General Specifications

Antenna Type	Sector
Band	Single band
Grounding Type	RF connector body grounded to reflector and mounting bracket
Performance Note	Outdoor usage
Radome Material	Fiberglass, UV resistant
Radiator Material	Low loss circuit board
Reflector Material	Aluminum
RF Connector Interface	4.3-10 Female
RF Connector Location	Bottom
RF Connector Quantity, low band	2
RF Connector Quantity, total	2

Remote Electrical Tilt (RET) Information

RET Hardware	CommRET v2
RET Interface	2x 8 pin connector as per IEC 60130-9 Daisy chain in: Male / Daisy chain out: Female Pin3: RS485A(AISG_B), Pin5: RS485B(AISG_A), Pin6: DC 10~30V, Pin7: DC_ Return
RET Interface, quantity	1 female 1 male
Input Voltage	10-30 Vdc
Internal RET	Low band (1)
Power Consumption, idle state, maximum	2 W
Power Consumption, normal conditions, maximum	10 W
Protocol	3GPP/AISG 2.0 (Single RET)
Dimensions	
Width	320 mm 12.598 in
Depth	140 mm 5.512 in



Page 1 of 5

2P-2L-C1

Length Net Weight, without mounting kit 2500 mm | 98.425 in 21 kg | 46.297 lb

Port Configuration



Electrical Specifications

Impedance	50 ohm
Operating Frequency Band	694 – 960 MHz
Polarization	±45°
Total Input Power, maximum	500 W

Electrical Specifications

Frequency Band, MHz	694–790	790-890	890-960
Gain, dBi	16.8	17.4	17.8
Beamwidth, Horizontal, degrees	69	66	63
Beamwidth, Vertical, degrees	8.9	7.8	7.2
Beam Tilt, degrees	3-12	3-12	3-12
USLS (First Lobe), dB	17	20	18
Front-to-Back Ratio, Copolarization 180° ± 30°, dB	31	33	31
Isolation, Cross Polarization, dB	28	28	28
Beamwidth, Horizontal, degrees Beamwidth, Vertical, degrees Beam Tilt, degrees USLS (First Lobe), dB Front-to-Back Ratio, Copolarization 180° ± 30°, dB	69 8.9 3–12 17 31	66 7.8 3–12 20 33	63 7.2 3–12 18 31

Page 2 of 5

©2024 CommScope, Inc. All rights reserved. CommScope and the CommScope logo are registered trademarks of CommScope and/or its affiliates in the U.S. and other countries. For additional trademark information see https://www.commscope.com/trademarks. All product names, trademarks and registered trademarks are property of their respective owners. Revised: November 9, 2023



2P-2L-C1

VSWR Return loss, dB	1.5 14.0	1.5 14.0	1.5 14.0
PIM, 3rd Order, 2 x 20 W, dBc	-153	-153	-153
Input Power per Port, maximum, watts	300	300	300

Electrical Specifications, BASTA

Frequency Band, MHz	694–790	790-890	890-960
Gain by all Beam Tilts, average, dBi	16.5	17.2	17.6
Gain by all Beam Tilts Tolerance, dB	±0.6	±0.4	±0.2
Beamwidth, Horizontal Tolerance, degrees	±2	±1.7	±1.3
Beamwidth, Vertical Tolerance, degrees	±0.6	±0.5	±0.3
USLS, beampeak to 20° above beampeak, dB	16	14	15
Front-to-Back Total Power at 180° ± 30°, dB	25	27	27
CPR at Boresight, dB	23	23	30
CPR at Sector, dB	14	8	12

Mechanical Specifications

Mechanical Tilt Range	0°-10°
Wind Loading @ Velocity, frontal	418.0 N @ 150 km/h (94.0 lbf @ 150 km/h)
Wind Loading @ Velocity, lateral	378.0 N @ 150 km/h (85.0 lbf @ 150 km/h)
Wind Loading @ Velocity, rear	915.0 N @ 150 km/h (205.7 lbf @ 150 km/h)
Wind Speed, maximum	241 km/h (150 mph)

Packaging and Weights

Width, packed	425 mm 16.732 in
Depth, packed	235 mm 9.252 in
Length, packed	2780 mm 109.449 in
Weight, gross	30.6 kg 67.461 lb

Regulatory Compliance/Certifications

Agency	Classification
CHINA-ROHS	Below maximum concentration value
ISO 9001:2015	Designed, manufactured and/or distributed under this quality management system
ROHS	Compliant
UK-ROHS	Compliant

Page 3 of 5

©2024 CommScope, Inc. All rights reserved. CommScope and the CommScope logo are registered trademarks of CommScope and/or its affiliates in the U.S. and other countries. For additional trademark information see https://www.commscope.com/trademarks. All product names, trademarks and registered trademarks are property of their respective owners. Revised: November 9, 2023



<u>2P-2L-C1</u>



Included Products

BSAMNT-B95-01	-	Wide Profile Antenna Downtilt Mounting Kit for 2.4 - 4.5 in (60 - 115 mm) OD round members.
		Kit contains one scissor top bracket set and one bottom bracket set.

* Footnotes

Performance Note Severe environmental conditions may degrade optimum performance

Page 4 of 5

©2024 CommScope, Inc. All rights reserved. CommScope and the CommScope logo are registered trademarks of CommScope and/or its affiliates in the U.S. and other countries. For additional trademark information see https://www.commscope.com/trademarks. All product names, trademarks and registered trademarks are property of their respective owners. Revised: November 9, 2023



BSAMNT-B95-01



Wide Profile Antenna Downtilt Mounting Kit for 2.4 - 4.5 in (60 - 115 mm) OD round members. Kit contains one scissor top bracket set and one bottom bracket set.

Product Classification	
Product Type	Downtilt mounting kit
General Specifications	
Application	Outdoor
Color	Silver
Dimensions	
Compatible Diameter, maximum	115 mm 4.528 in
Compatible Diameter, minimum	61 mm 2.402 in
Material Specifications	
Material Type	Galvanized steel
Dackaging and Mojepte	

Packaging and Weights

Included	Brackets Hardware
Packaging quantity	2
Weight, gross	3.6 kg 7.937 lb

Regulatory Compliance/Certifications

Agency	Classification
CE	Compliant with the relevant CE product directives
ISO 9001:2015	Designed, manufactured and/or distributed under this quality management system
C E ISO 9001:2015	

Page 5 of 5

©2024 CommScope, Inc. All rights reserved. CommScope and the CommScope logo are registered trademarks of CommScope and/or its affiliates in the U.S. and other countries. For additional trademark information see https://www.commscope.com/trademarks. All product names, trademarks and registered trademarks are property of their respective owners. Revised: November 7, 2023

